



Mixer Amplifier (Phone Jack MIC Input)

T-35M



Features

- * 3 MIC inputs, 2 AUX inputs.
- * 3 MIC volume control, 2 AUX volume control.
- * With priority, MIC1 input is prior to other audio inputs.
- * Separate treble and bass adjustment knob.
- * One MIC2 / AUX1 selector switch, one MIC3 / AUX2 selector switch.
- * Two types of power output: 4 ohm, 8 ohm and 70V, 100V output.
- * Single-channel rated power 35W / 60W output.

Specifications

Model	T-35M
Rated Power Output	35W
Speaker Outputs	70V, 100V & 4-8Ω
Input Sensitivity & Impedance	MIC 1, 2, 3: 5mV/600Ω MIC2: 775mV/10KΩ AUX2: 350mV/10KΩ
Output Sensitivity & Impedance	MIX OUT: 1V/470Ω
Tone	Bass: ±10dB at 100Hz Treble: ±10dB at 10KHz
Frequency Response	50Hz~16KHz (+1dB, -3dB)
S/N Ratio	MIC 1, 2, 3: 66dB, AUX 1, 2: 80dB
THD	Less than 0.5% at 1KHz, 1/3 rated power
Crosstalk	≤50dB
Cooling	Fan automatically start up when temp reaches 55°C
Protection	High temp, overload & short-circuit
Power Supply	~110V-230V 50/60Hz
Power Consumption	60W
Weight	3Kg
Dimensions	484 x 335 x 88mm
Finish	Panel: aluminum plate, black Case: SPCC Panel

Rear Panel

