



Infrared Battery Charging Unit

TS-0670HC



Description

*Digital infrared battery charging unit is used for charging , the red light means battery and charging stand is in poor connection; if charging indicator light is orange, it means the unit is in charging ; if charging indicator light turns green, it means the battery has been fully charged.

Feature

- *It can simultaneously charge 30 units.
- *Power input with concatenated function.
- *Quick Charging is 3 hours: the maximum charge time is 8 hours.
- *Charging unit is not only for charging function, but also for keeping the receivers.

Model	TS-0670HC
Input Voltage	~100V-240V 50-60Hz
The Maximum Power Consumption	100W
Standby Power Consumption	17W
Dimension(mm)	627(L)×385(W)×238(H)
Weight	10Kg